



用途：主要用于节能灯、日光灯电子镇流器及其它开关、振荡电路。

Purpose: High frequency electronic lighting ballast applications, converters, inverters, switching regulators, etc.

极限参数/Absolute maximum ratings ($T_a=25^\circ\text{C}$)

参数符号 Symbol	数值 Rating	单位 Unit
V_{CB0}	600	V
V_{CE0}	400	V
V_{EB0}	9.0	V
I_C	0.5	A
$P_C(T_a=25^\circ\text{C})$	1.0	W
T_j	150	$^\circ\text{C}$
T_{sag}	-55~150	$^\circ\text{C}$




引脚: 1. E 2. C 3. B

电性能参数/Electrical characteristics ($T_a=25^\circ\text{C}$)


参数符号 Symbol	测试条件 Test condition		数值 Rating			单位 Unit
			最小值 Min	典型值 Typ	最大值 Max	
V_{CB0}	$I_C=1\text{mA}$	$I_E=0$	600			V
V_{CE0}	$I_C=10\text{mA}$	$I_B=0$	400			V
V_{EB0}	$I_E=1\text{mA}$	$I_C=0$	9.0			V
I_{CB0}	$V_{CB}=600\text{V}$	$I_E=0$			0.1	mA
I_{CE0}	$V_{CE}=400\text{V}$	$I_B=0$			0.1	mA
I_{EB0}	$V_{EB}=9.0\text{V}$	$I_C=0$			0.1	mA
h_{FE}	$V_{CE}=5\text{V}$	$I_C=100\text{mA}$	10		40	
$V_{CE(\text{sat})}$	$I_C=100\text{mA}$	$I_B=20\text{mA}$			0.5	V
$V_{BE(\text{sat})}$	$I_C=100\text{mA}$	$I_B=20\text{mA}$			1.2	V
t_f	$V_{CE}=5\text{V}$	$I_C=0.1\text{A}$			0.8	μS
t_s	(UI9600)				3.0	μS
f_T	$V_{CE}=10\text{V}$	$I_C=50\text{mA}$	$f=1\text{MHz}$	5		MHz

MJE13001DE1 (3DD13001DE1)


SOA (DC)




$P_c - T_c$




$h_{FE} - I_c$




$h_{FE} - I_c$




$V_{ces} - I_c$



$V_{bes} - I_c$



$t_s - T_a$



$h_{FE} - T_a$

