PD-94313D

International
IOR Rectifier

IRG4MC30F

INSULATED GATE BIPOLAR TRANSISTOR

Fast Speed IGBT

Features

- Electrically Isolated and Hermetically Sealed
- Simple Drive Requirements
- Latch-proof
- Fast Speed Operation 3 kHz - 8 kHz
- High Operating Frequency
- Switching-loss Rating includes all "tail" losses
- Ceramic Eyelets



n-channel

V_{CES} = 600V

$V_{CE(on)\ max}$ =1.7V

@V_{GE} = 15V, I_C = 15A

Benefits

- Generation 4 IGBT's offer highest efficiency available
- IGBT's optimized for specified application conditions
- Designed to be a "drop-in" replacement for equivalent IR Hi-Rel Generation 3 IGBT's

Insulated Gate Bipolar Transistors (IGBTs) from International Rectifier have higher usable current densities than comparable bipolar transistors, while at the same time having simpler gate-drive requirements of the familiar power MOSFET. They provide substantial benefits to a host of high-voltage, high-current applications.

TO-254AA

Absolute Maximum Ratings

	Parameter	Max.	Units
V_{CES}	Collector-to-Emitter Breakdown Voltage	600	V
I_C @ T_C = 25°C	Continuous Collector Current	28	A
I_C @ T_C = 100°C	Continuous Collector Current	15	
I_{CM}	Pulsed Collector Current ①	112	
I_{LM}	Clamped Inductive Load Current ②	112	
V_{GE}	Gate-to-Emitter Voltage	± 20	V
P_D @ T_C = 25°C	Maximum Power Dissipation	75	W
P_D @ T_C = 100°C	Maximum Power Dissipation	30	
T_J T_{STG}	Operating Junction and Storage Temperature Range	-55 to + 150	°C
	Lead Temperature	300 (0.063in./1.6mm from case for 10s)	
	Weight	9.3 (typical)	g

Thermal Resistance

	Parameter	Min	Typ	Max	Units	Test Conditions
R_{thJC}	Junction-to-Case	—	—	1.67	°C/W	

01/10/13

Electrical Characteristics @ T_J = 25°C (unless otherwise specified)

	Parameter	Min.	Typ.	Max.	Units	Conditions
$V_{(BR)CES}$	Collector-to-Emitter Breakdown Voltage	600	—	—	V	V_{GE} = 0V, I_C = 1.0 mA
$V_{(BR)ECS}$	Emitter-to-Collector Breakdown Voltage ③	18	—	—	V	V_{GE} = 0V, I_C = 1.0 A
$\Delta V_{(BR)CES}/\Delta T_J$	Temperature Coeff. of Breakdown Voltage	—	0.63	—	V/°C	V_{GE} = 0V, I_C = 1.0 mA
$V_{CE(ON)}$	Collector-to-Emitter Saturation Voltage	—	—	1.7	V	I_C = 15A V_{GE} = 15V
		—	—	2.2		I_C = 28A See Fig.2, 5
		—	—	2.7		I_C = 15A , T_J = 125°C
$V_{GE(th)}$	Gate Threshold Voltage	3.0	—	6.0		V_{CE} = V_{GE}, I_C = 1.0 mA
$\Delta V_{GE(th)}/\Delta T_J$	Temperature Coeff. of Threshold Voltage	—	-11	—	mV/°C	V_{CE} = V_{GE}, I_C = 250 µA
g_{fe}	Forward Transconductance ④	14	—	—	S	V_{CE} ≥ 15V, I_C = 15A
I_{CES}	Zero Gate Voltage Collector Current	—	—	50	µA	V_{GE} = 0V, V_{CE} = 480V
		—	—	1000		V_{GE} = 0V, V_{CE} = 480V, T_J = 125°C
I_{GES}	Gate-to-Emitter Leakage Current	—	—	±100	nA	V_{GE} = ±20V

Switching Characteristics @ T_J = 25°C (unless otherwise specified)

	Parameter	Min.	Typ.	Max.	Units	Conditions
Q_g	Total Gate Charge (turn-on)	—	—	77	nC	I_C = 15A
Q_{ge}	Gate - Emitter Charge (turn-on)	—	—	12		V_{CC} = 300V See Fig. 8
Q_{gc}	Gate - Collector Charge (turn-on)	—	—	24		V_{GE} = 15V
$t_{d(on)}$	Turn-On Delay Time	—	—	42	ns	T_J = 25°C
t_r	Rise Time	—	—	30		I_C = 15A, V_{CC} = 480V
$t_{d(off)}$	Turn-Off Delay Time	—	—	300		V_{GE} = 15V, R_G = 7.5Ω
t_f	Fall Time	—	—	300		Energy losses include "tail"
E_{ts}	Total Switching Loss	—	—	2.0	mJ	See Fig. 10, 11, 13, 14
$t_{d(on)}$	Turn-On Delay Time	—	—	42	ns	T_J = 125°C,
t_r	Rise Time	—	—	20		I_C = 15A, V_{CC} = 480V
$t_{d(off)}$	Turn-Off Delay Time	—	—	450		V_{GE} = 15V, R_G = 7.5Ω
t_r	Rise Time	—	—	550		Energy losses include "tail"
E_{ts}	Total Switching Loss	—	—	3.0	mJ	See Fig. 13, 14
$L_C + L_E$	Total Inductance	—	6.8	—	nH	Measured from Collector lead (6mm/ 0.25in. from package) to Emitter lead (6mm / 0.25in. from package)
C_{ies}	Input Capacitance	—	1100	—	pF	V_{GE} = 0V
C_{oes}	Output Capacitance	—	74	—		V_{CC} = 30V See Fig. 7
C_{res}	Reverse Transfer Capacitance	—	14	—		f = 1.0MHz

Notes:

① Repetitive rating; V_{GE} = 20V, pulse width limited by max. junction temperature. (See Fig. 13b)

② V_{CC} = 80%(V_{CES}), V_{GE} = 20V, L = 100µH, R_G = 7.5Ω, (See Fig. 13a)

③ Pulse width ≤ 80µs; duty factor ≤ 0.1%.

④ Pulse width 5.0µs, single shot.



Fig. 1 - Typical Load Current vs. Frequency
(For square wave, $I=I_{RMS}$ of fundamental; for triangular wave, $I=I_{PK}$)



Fig. 2 - Typical Output Characteristics



Fig. 3 - Typical Transfer Characteristics



Fig. 4 - Maximum Collector Current vs. Case Temperature



Fig. 5 - Collector-to-Emitter Voltage vs. Junction Temperature



Fig. 6 - Maximum Effective Transient Thermal Impedance, Junction-to-Case



Fig. 7 - Typical Capacitance vs. Collector-to-Emitter Voltage



Fig. 8 - Typical Gate Charge vs. Gate-to-Emitter Voltage



Fig. 9 - Typical Switching Losses vs. Gate Resistance



Fig. 10 - Typical Switching Losses vs. Junction Temperature



Fig. 11 - Typical Switching Losses vs. Collector-to-Emitter Current



Fig. 12 - Turn-Off SOA



Fig. 13a - Clamped Inductive Load Test Circuit



Fig. 13b - Pulsed Collector Current Test Circuit



Fig. 14a - Switching Loss Test Circuit

*** Driver same type as D.U.T., VC = 720V**



Fig. 14b - Switching Loss Waveforms

Case Outline and Dimensions — TO-254AA



NOTES:

1. DIMENSIONING & TOLERANCING PER ASME Y14.5M-1994.
2. ALL DIMENSIONS ARE SHOWN IN MILLIMETERS [INCHES].
3. CONTROLLING DIMENSION: INCH.
4. CONFORMS TO JEDEC OUTLINE TO-254AA.

PIN ASSIGNMENTS

1 = COLLECTOR
2 = EMITTER
3 = GATE

CAUTION

BERYLLIA WARNING PER MIL-PRF-19500

Package containing beryllia shall not be ground, sandblasted, machined, or have other operations performed on them which will produce beryllia or beryllium dust. Furthermore, beryllium oxide packages shall not be placed in acids that will produce fumes containing beryllium.

International
IOR Rectifier

IR WORLD HEADQUARTERS: 101 N. Sepulveda Blvd., El Segundo, California 90245, USA Tel: (310) 252-7105
IR LEOMINSTER : 205 Crawford St., Leominster, Massachusetts 01453, USA Tel: (978) 534-5776
TAC Fax: (310) 252-7903
Visit us at www.irf.com for sales contact information.
Data and specifications subject to change without notice. 01/2013