


SILICON BRIDGE RECTIFIER 1 AMP, 100 THRU 1000 VOLTS





www.centralsemi.com

DESCRIPTION:

The CENTRAL SEMICONDUCTOR CBR1-D010 series types are full wave silicon bridge rectifiers mounted in a durable epoxy molded case. These devices are ideal for printed circuit board mounting and fit into a standard DIP socket (0.1"/2.54mm spacing).

NOTE: Also available in fast recovery. Please contact factory for details.

MARKING: FULL PART NUMBER

MAXIMUM RATINGS: (T_A=25°C unless otherwise noted))

·····		CBR1	CBR1	CBR1	CBR1	CBR1	CBR1	
	SYMBOL	<u>-D010</u>	<u>-D020</u>	<u>-D040</u>	-D060	-D080	<u>-D100</u>	UNITS
Peak Repetitive Reverse Voltage	VRRM	100	200	400	600	800	1000	V
DC Blocking Voltage	VR	100	200	400	600	800	1000	V
RMS Reverse Voltage	V _{R(RMS)}	70	140	280	420	560	700	V
Average Forward Current (T _A =50°C)	Ι _Ο			1	.0			А
Peak Forward Surge Current	IFSM			5	0			А
Operating and Storage								
Junction Temperature	TJ, Tstg			-65 to	+150			°C
		-0500			- 4			

ELECTRICA	AL CHARACTERISTICS PER DIODE	: (T _A =25°C unless oth	erwise noted)	
SYMBOL	TEST CONDITIONS	MIN	MAX	UNITS
IR	V _R =Rated V _{RRM}		10	μΑ
VF	I _F =1.0A		1.1	V


R3 (11-June 2012)



CBR1-D010 SERIES

SILICON BRIDGE RECTIFIER 1 AMP, 100 THRU 1000 VOLTS

DIP CASE - MECHANICAL OUTLINE



CHES MAX 0 0.350 5 0.315 6 0.098 6 0.335	MIN 7.62 7.24 2.18	METERS MAX 8.89 8.00 2.49
0.350 0.315 0.098	7.62 7.24 2.18	8.89 8.00 2.49
5 0.315 6 0.098	7.24 2.18	8.00 2.49
6 0.098	2.18	2.49
0 335	0 02	0.54
0.000	8.03	8.51
0.045	0.89	1.14
3 0.022	0.46	0.56
0.205	4.95	5.21
0.255	6.22	6.48
0.075	1.40	1.91
0.185	3.81	4.70
	0.205 0.255 0.255 0.075	5 0.205 4.95 5 0.255 6.22 5 0.075 1.40

DIP (REV: R1)

MARKING: FULL PART NUMBER

R3 (11-June 2012)

www.centralsemi.com